

W2D

Wire-Free Camera Base Station with Built-in Siren



Introduction

The Wire-Free Camera Base Station is the gateway for wire-free Cameras to extend both wireless coverage and extra battery life of wire-free camera. The base station can access up to 6 wire-free cameras.

Built-in siren can be triggered by PIR motion detections on wire-free camera, together with an instant alert on your phone. Answer the alert, and you can see, hear and speak to people in front of the camera from anywhere.

Main Features



Supports access up to 6 FHD resolution wire-free cameras



Prolong the overall battery life of the cameras by utilizing the extra low power consumption standby mode



Extend the coverage for wire-free Cameras



100 decibel siren on the base station can be triggered when PIR motion is detected



Wired connection to router

Specifications

| | |
|---|---|
| Model | CS-W2D-EUP Wire-Free Camera Base Station with Built-in Siren |
| Network Interface | 1 RJ-45 10/100Mbps Self-adaptive Ethernet WAN interface. |
| Wireless Interface | Support 2.4G connection. The actual available channels vary according to the sales area regulations. Theoretical maximum rate is 144M at 802.11b/g/n. Support Sub-1G connection with Low-Power Private Protocol. Working Band of 433M/868M/915M and available channels vary according to the sales area regulations. |
| Battery Camera | Support up to 6 Wire-Free Cameras |
| CPU | Qualcomm @ 650 MHz (Maximum) |
| RAM | 128MB |
| Flash | 16 MB |
| Alarm Siren | Supported |
| Antenna | 2.4G: 2 internal @ 2dB max Sub-1G: 1 internal |
| Indicator | One System LED One WAN Port LED |
| Button | One SYNC button. One Power button. One Reset button, hold 10 seconds to RESET. |
| Power | DC 5V 2A, typical power consumption < 10watts The adapter supports a wide voltage range, expected 100V~240V |
| Working Temperature and Humidity | 0 °C to +40 °C, 10% to 90%. Indoor use only. |
| Dimension | 95 * 95 *110 mm |
| Weight | 180g |